

THE ORIGINAL SINCE 1967

cry baby
CANTRELL®

LIVE TO PLAY LIVE®



JIMDUNLOP.COM

92503009532revB

JC95 JERRY CANTRELL CRY BABY® WAH WAH

POWER

The Jerry Cantrell Signature Cry Baby® Wah Wah is powered by one 9-volt battery (accessed via the bottom of the pedal), an AC adapter such as the Dunlop ECB003/ECB003E, or a DC Brick™ power supply.

SETUP INSTRUCTIONS

- Run a shielded instrument cable from your guitar to the JC95's INSTRUMENT jack.
- Run another shielded instrument cable from the JC95's AMPLIFIER jack to your amplifier input.
- Turn on the amplifier and begin playing.
- To turn the pedal on/off, push the toe of the pedal down until you feel a "click."
- Rotate the FINE TUNE knob clockwise for a brighter toe-down response or counterclockwise for a darker toe-down response.

SPECIFICATIONS

Impedance

Input	1 M Ω
Output	10 k Ω

Filter Center Frequency

Heel Down	320 Hz to 390 Hz
Toe Down	
Fine Tune Max	1700 Hz to 2070 Hz
Fine Tune Min	1050 kHz to 1270 Hz

Maximum Level

Input	-11.5 dBV
Output	+6 dBV

Maximum Gain at Center Frequency

Heel Down	+18 dB
Toe Down	+20 dB

Noise Floor*

Heel Down	>97 dB
Toe Down	>89 dB

Bypass	Hardwire
---------------	----------

Current Draw	1 mA
---------------------	------

Power Supply	9 volts DC
---------------------	------------

*V_{REF}=1V_{RMS}, A-weighted

